



## Explosion Proof EF24 Transmitter (only) 6 Buttons 2 Speed

### Especificaciones Técnicas

<b>Channels</b>	6	<b>Control Speed</b>	2 Speed
<b>Transmitter Emergency Stop</b>	Yes	<b>Codigo FCC</b>	OFNF21
<b>Fuente de Alimentación del Transmisor</b>	4 AA batteries	<b>Distancia de Control</b>	300 ft up to 600 ft with optional antenna
<b>Código de Seguridad</b>	32 bits (4.3 billion)	<b>Potencia del Transmisor</b>	≤10dBm
<b>Rango de Frecuencia</b>	VHF: 310~331 MHz; UHF: 425 ~ 446 MHz	<b>Rango de temperatura de Trabajo</b>	-40 ~ 185 °F / -40 ~ 85°C
<b>Normas</b>	FCC and OSHA standard 1910.179	<b>Garantía</b>	1 Year

**EF-24 TRANSMITTER**  
Explosion-proof design



MODEL: EF24-TX  
ITEM CODE: 924-400-001  
Dimension: 186 x 61 x 51 mm  
Weight: 280g (without batteries)



**Product features**


- 10 double steps pushbuttons + EMERGENCY STOP + START KEY + SPARE
- 20 control contactors
- Battery voltage warning device, the power supply is cut off during low power
- Safety key switch is to prevent from unauthorized users
- Program the button function by computer interface
- Up/down, east/west, south/north can be programmed to interlock or non-interlock
- Start key can be programmed to start, toggle switch, normal or other functions
- The spare buttons can be programmed to start, toggle, interlock or normal, etc

**Standard Configuration**

- One transmitter (with hanging belt)
- One dust bag
- One receiver
- Receiver is with 1.6 meter cable
- Battery: one pair
- One receive antenna
- Operation and maintenance manual

**Dual power supply:**

EF24 is new series explosion-proof radio remote control based on F24 series, strictly complies with explosion-proof criterion GB3638.1 and GB3836.4, and has passed EXiII BT4 intrinsic safety certification, can operate safely in the chemical and petrochemical industries, mining and other flammable, explosive and hazardous environments.



**Peso & Dimensiones**

Peso Total

1 lbs / 1 Kg

Referential Images / Imágenes Referenciales  
Specifications may change without notice / las especificaciones pueden cambiar sin previo aviso