



## Radio Remote Control 4 Channels 2 Speed Multi voltage Range 300 ft

### Características Esenciales

- 200 Auto Channels replacing traditional single channel quartz plus 1 Million ID Codes.
- Easy Pairing System, no need of software or copier to add or replace lost or broken Transmitter
- Customizable 200 Functions settings to meet any special requirements
- Reinforced fiber plastic case for Transmitter and Receiver plus rubber protector for Transmitter

## Especificaciones Técnicas

Transmitter Emergency Stop	Yes	Control Speed	2 Speed
Channels	4	Código FCC	2AZMK-Q1212
Botones	5	Fuente de Alimentación del Transmisor	2 AA batteries
Fuente de Alimentación del Receptor	AC 110V-480V	Sensibilidad del Receptor	dBm -112
Distancia de Control	300 ft / 100 mt	Código de Seguridad	200 Millions
Potencia del Transmisor	≤10dBm	Rango de Frecuencia	433/480 MHz
Rango de temperatura de Trabajo	-40 ~ 185 °F / -40 ~ 85°C	Normas	FCC and OSHA standard 1910.179
Garantía	1 Year	Wireless Control IP Protection	IP65

## Peso & Dimensiones

**Peso Total** 4 lbs / 2 Kg

## Detalles del Empaque

**A Altura Total** 5.3

**D Depth** 1.2

**W Ancho** 2.7

Referential Images / Imágenes Referenciales  
Specifications may change without notice / las especificaciones pueden cambiar sin previo aviso