



## Control Remoto largo alcance 300 m - 8 Botones Una Velocidad - Multivoltage

### Características Esenciales

- 200 Auto Channels replacing traditional single channel quartz plus 1 Million ID Codes.
- Easy Pairing System, no need of software or copier to add or replace lost or broken Transmitter
- Customizable 200 Functions settings to meet any special requirements
- Reinforced fiber plastic case for Transmitter and Receiver plus rubber protector for Transmitter

### Especificaciones Técnicas

<b>Transmitter Emergency Stop</b>	Yes	<b>Control Speed</b>	1 Speed
<b>Channels</b>	8	<b>Codigo FCC</b>	2AZMK-Q1212
<b>Capacidad Contactor</b>	10A	<b>Botones</b>	9
<b>Fuente de Alimentación del Transmisor</b>	2 AA batteries	<b>Fuente de Alimentación del Receptor</b>	AC 110V-480V
<b>Sensibilidad del Receptor</b>	dBm -112	<b>Distancia de Control</b>	900 ft / 300 mt
<b>Código de Seguridad</b>	200 Millions	<b>Potencia del Transmisor</b>	≤10dBm
<b>Rango de Frecuencia</b>	433/480 MHz	<b>Rango de temperatura de Trabajo</b>	-40 ~ 185 °F / -40 ~ 85°C
<b>Normas</b>	FCC and OSHA standard 1910.179	<b>Garantía</b>	1 Year
<b>Wireless Control IP Protection</b>	IP65		

## Peso & Dimensiones

**Peso Total** 4 lbs / 2 Kg

## Detalles del Empaque

**A Altura Total** 6.68

**D Depth** 0.6

**W Ancho** 2.1

Referential Images / Imágenes Referenciales  
Specifications may change without notice / las especificaciones pueden cambiar sin previo aviso